



2 CH Dante Wall Plate

Dpanel

1. Built-in DANTE module, analog signal to Dante digital signal for transfer.
2. Dual-channel input phantom power switch.
3. Dual-channel input gain adjustment.
4. Dual-channel two-in-one Canon input interface.
5. Standard 120 type pre-built box installation.

Sampling Rate	48KHz	Phantom power	48V
Frequency Response	20-20K Hz, $\pm 0.5\text{dB}$	THD+N	$\leq 0.005\%$ @4dBu
Input Impedance (Balanced)	20k Ω	Output Impedance (Balanced)	100 Ω
Channel Isolation	100dB @1k Hz	Common Mode Rejection	80dB @80 Hz
Maximum Line Input	20dBu	Maximum Line Output	11dBu
Background Noise	-90dBu	Operating Power Supply	PoE Power Supply

